

Movelite WireFree RTS

Quick Installation Guide


1. Connect motor to the Rail




2. Connect battery Pack



3. Charge the battery







1.LED is red : charge in on-going. 2.LED is green: charge is finished.

4. How to set

4.1. Pre-program the RTS remote control



Press Open and Close buttons at the same time on the RTS remote control: the motorized product moves briefly and the RTS remote control is pre-programmed into the motor.

4.2. Set the limits

Press Open 🔲 or Close 🔳 , the motorized product makes a first run to record the hard stop positions.


4.3. Record the RTS control point



Press the PROG button on the back of the remote control until the motorized product moves. The remote control address is permanently recorded. Your product is now ready to use.

5. How to use

5.1. Open / Close functions



5.2. Stop function



When the motorized product is moving, briefly press my: the motorized product stops automatically.

5.3. Favorite (my) position



The motorized product is stopped. Briefly press my: the motorized product starts to move and stops in the favorite (my) position. If no motion, please refer to the instructions to set (my) position.

6. Tips and recommendations

Observations	Possible causes	Solutions
The motorised product does not operate.	The battery pack is weak.	Check whether the battery pack is weak and charge it.
	The remote control battery is weak.	Check whether the battery is weak and replace it if necessary.
	The remote control is not compatible.	Check for compatibility and replace the remote control if necessary.
	The remote control used has not been programmed into the motor.	Use a programmed remote control or program this remote control.

Remarks: For the detailed information, please refer to the instructions.